

## CD223NRB

100A 2P Type3R 120/240VAC General Duty Safety Switch with Solid Neutral



### Main

|                           |                            |
|---------------------------|----------------------------|
| Product or component type | Single Throw Safety Switch |
| Series name               | General duty               |

### Complementary

|                                |  |
|--------------------------------|--|
| [In] rated current             | 100 A  |
| Disconnecter device type       | Fusible disconnect                                       |
| Short-circuit current          | Cartridge 100 kA (maximum)                               |
| Device mounting                | Surface  |
| Number of poles                | 2  |
| Electrical connection          | Lugs   |
| [Ue] rated operational voltage | 120/240 V AC   |
| AWG gauge                      | AWG 14...AWG 10 (copper)<br>AWG 12...AWG 1/0 (aluminium) |

### Environment

|                           |                          |
|---------------------------|--------------------------|
| product certifications    | CSA                      |
| NEMA degree of protection | NEMA 3R galvanized steel |

### Offer Sustainability

|                                  |   |
|----------------------------------|---|
| Sustainable offer status         | Green Premium product   |
| RoHS (date code: YYWW)           | Compliant - since 1313 - Schneider Electric declaration of conformity |
| REACH                            | Reference not containing SVHC above the threshold                     |
| Product environmental profile    | Available   |
| Product end of life instructions | Need no specific recycling operations                                 |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.