



Main

| | |
|--------------------------------|-------------------------------------|
| Product or component type | Miniature circuit-breaker |
| Range of product | QO |
| Line Rated Current | 70 A |
| System Voltage | 120 V AC 120/240 V AC 48 V DC |
| Mounting mode | Bolt-on |
| Poles description | 2P |
| Circuit breaker type | Standard |
| Circuit breaker application | HACR rated |
| Electrical connection | Box lugs |
| Accessory / separate part type | Shunt trip, 120/208/240 V AC, |

Complementary

| | |
|---------------------------|--------------------------------------------------------------------------------------------------------|
| Breaking capacity | 5 kA at: 48 V DC 5 kA at: 48 V DC 10 kA at: 120/240 V AC 50/60 Hz 10 kA at: 120 V AC 50/60 Hz |
| Number of spaces required | 3 |
| AWG gauge | AWG 8...AWG 2 (copper or aluminium) |
| Height | 3.12 in |
| Depth | 2.91 in |
| Width | 2.25 in |

Environment

| | |
|---------------------------------------|------------------|
| product certifications | CSA UL listed |
| ambient air temperature for operation | 104 °F (40 °C) |

Offer Sustainability

| | |
|--------------------------------------------------------------------------|-----------------------------------------------------------------------|
| Green Premium product | Green Premium product |
| Compliant - since 1323 - Schneider Electric declaration of conformity | Compliant - since 1323 - Schneider Electric declaration of conformity |
| Reference contains SVHC above the threshold - go to CaP for more details | Reference contains SVHC above the threshold |
| Available | Available |
| Need no specific recycling operations | Need no specific recycling operations |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.