

# CLASS 2 ENCLOSED ELECTRONIC

## Transformers

# WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project: \_\_\_\_\_

Location: \_\_\_\_\_

### PRODUCT DESCRIPTION

Combining Class 2 Transformers in a single package creates a single source to wire multiple runs of low voltage fixtures such as under cabinet and display luminaires.

### FEATURES

- 1W minimum load
- Secondary wiring for Class 2 transformers does not require conduit sheathed cable or clamp wiring techniques
- Intrinsically safe, Class 2 transformers permit no greater than a 5 amp current be drawn
- Non-metallic sheathed cable may be used for secondary wiring in walls and ceilings
- Drop down to a smaller gauge wire if space in fixture does not permit secure connection directly with the non-metallic sheathed cable
- Powers most cabinet fixtures

### SPECIFICATIONS

**Construction:** Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

**Output:** 12V / 24V

**Frequency:** 20khz

**Dimming:** Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer.

**Details:** Enclosure has knockouts on three sides. Screw holes are located on one long side for securing enclosure in place.

**Standards:** UL Listed

### ORDER NUMBER

Model	Output	L	W	H
EN-1260-RB2	12V, 60W	6 <sup>5</sup> / <sub>8</sub> "	1 <sup>5</sup> / <sub>8</sub> "	1 <sup>1</sup> / <sub>8</sub> "
EN-2460-RB2	24V, 60W	6 <sup>5</sup> / <sub>8</sub> "	1 <sup>5</sup> / <sub>8</sub> "	1 <sup>1</sup> / <sub>8</sub> "
EN-24100-RB2	24V, 96W	6 <sup>5</sup> / <sub>8</sub> "	1 <sup>5</sup> / <sub>8</sub> "	1 <sup>1</sup> / <sub>8</sub> "
EN-12120-RB2*	12V, 2 x 60W	6"	3 <sup>1</sup> / <sub>4</sub> "	2 <sup>5</sup> / <sub>8</sub> "
EN-12180-RB2*	12V, 3 x 60W	6 <sup>3</sup> / <sub>4</sub> "	3 <sup>5</sup> / <sub>8</sub> "	2 <sup>5</sup> / <sub>8</sub> "
EN-12300-RB2*	12V, 5 x 60W	8 <sup>1</sup> / <sub>4</sub> "	4 <sup>5</sup> / <sub>8</sub> "	2 <sup>5</sup> / <sub>8</sub> "

\*Includes LED indicator lights and integral push-in terminals

**EN** -  -

Example: EN-12180-RB2

### ACCESSORIES

#### Multiple Terminal Block

Accommodates up to 6 output connections for 14 AWG wires. Terminal block is used to easily wire together multiple output connections for a neat under cabinet installation without the use of open splices. Perfect for wiring up to 3 button lights at 20W or 6 button lights at 10W.

Model	L	W	H
MTB-01	3 <sup>1</sup> / <sub>4</sub> "	1 <sup>3</sup> / <sub>4</sub> "	7 <sup>8</sup> / <sub>8</sub> "

### WAC Lighting

www.waclighting.com

Phone (800) 526.2588 • Fax (800) 526.2585

### Headquarters/Eastern Distribution Center

44 Harbor Park Drive • Port Washington, NY 11050

Phone (516) 515.5000 • Fax (516) 515.5050

### Western Distribution Center

1750 Archibald Avenue • Ontario, CA 91760

Phone (800) 526.2588 • Fax (800) 526.2585