

**Product datasheet**  
Characteristics

# QO220GFI

Mini CB - QO - 20A - 2P - 120/240V - 10kA - Plug-in  
- GFI



### Main

|                                |                                      |
|--------------------------------|--------------------------------------|
| Product or component type      | Miniature circuit-breaker            |
| Range of product               | QO                                   |
| [In] rated current             | 20 A                                 |
| [Ue] rated operational voltage | 120 V AC<br>120/240 V AC             |
| Mounting mode                  | Plug-in                              |
| Poles description              | 2P                                   |
| Circuit breaker type           | Ground fault protecting class A 6 mA |
| Circuit breaker application    | Not rated                            |
| Electrical connection          | Pressure plate                       |

### Complementary

|                           |  |
|---------------------------|--|
| Breaking capacity         | 10 kA at: 120/240 V AC 50/60 Hz<br>10 kA at: 120 V AC 50/60 Hz |
| Number of spaces required | 2  |
| AWG gauge                 | AWG 14...AWG 8 (copper)<br>AWG 12...AWG 8 (aluminium)          |
| Height                    | 4.12 in  |
| Depth                     | 2.91 in  |
| Width                     | 1.5 in   |

### Environment

|                                       |                  |
|---------------------------------------|------------------|
| product certifications                | CSA<br>UL listed |
| ambient air temperature for operation | 40 °C            |

### Offer Sustainability

|                                  |   |
|----------------------------------|---|
| Sustainable offer status         | Green Premium product   |
| RoHS (date code: YYWW)           | Compliant - since 1340 - Schneider Electric declaration of conformity |
| REACH                            | Reference contains SVHC above the threshold                           |
| Product environmental profile    | Available   |
| Product end of life instructions | Available   |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.