


CHOM215GFI

HOMELINE CIRCUIT BREAKER 120V 15A 2P
GROUND FAULT INTERRUPTER 5mA



Main

| | |
|--------------------------------|---|
| Range of product | Homeline |
| Product or component type | Miniature circuit-breaker |
| [In] rated current | 15 A |
| [Ue] rated operational voltage | 120/240 V AC |
| Mounting mode | Plug-on |
| Poles description | 2P |
| Short-circuit current | 10 kA |
| Circuit breaker type | Ground fault protecting : 6 mA ,class A |
| Circuit breaker application | HACR rated |
| Electrical connection | Screw clamp terminals |

Complementary

| | |
|---------------------------|-----------------------------------|
| Number of spaces required | 2 |
| AWG gauge | AWG 12...AWG 4 (aluminium/copper) |

Environment

| | |
|---------------------------------------|-------|
| product certifications | CSA |
| ambient air temperature for operation | 40 °C |

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1340 - Schneider Electric declaration of conformity |
| REACH | Reference contains SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Available |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.