

Product datasheet
Characteristics

NQ30L1C

NQ Pnlbrd Interior 100A, 1 PH, 3 Wire, 30 CCT, Mn Lug, Cu



Main

| | |
|----------------------|----------------------|
| Load center type | Main lugs |
| Circuit breaker type | QOB QOB-VH QHB |
| Material | Copper |

Complementary

| | |
|--------------------------------|---|
| Number of spaces | 30 |
| Enclosure nominal height | 32 in |
| Enclosure nominal width | 20 in |
| Enclosure nominal depth | 5.75 inFor NEMA 1 enclosure 6.5 inFor NEMA 3R/5/12 enclosure |
| [In] rated current | 100 A |
| Wiring configuration | 3-wire |
| Network number of phases | 1 phase |
| [Ue] rated operational voltage | 240 V AC 48 V DC |

Environment

| | |
|-----------|--------------------|
| standards | CSA C22.2 UL 67 |
|-----------|--------------------|

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1419 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.