

**Plug-On Circuit Breakers, Types BR**  
**10,000/22,000/42,000 Amperes**  
**Interrupting Capacity 120, 120/240 or 240V AC**



BR120



BR215



BR320

**Type BR Breakers, 1-Inch (25.4 mm) per Pole 120, 120/240 or 240V AC, 10,000, 22,000 or 42,000 AIC**

Note: All Type BR 1-, 2-, and 3-pole circuit breakers carry listing for HACR application.  
 For circuit breakers with a shunt trip, add ST suffix.

Ampere Rating	Wire Size Range Cu/Al 60°C or 75°C AWG	1-Pole 120/240V AC Requires One 1-Inch (25.4 mm) Space		2-Pole 120/240V AC Common Trip Requires Two 1-Inch (25.4 mm) Spaces			3-Pole 240V AC Common Trip Requires Three 1-Inch (25.4 mm) Spaces	
		10 per Shelf Carton		5 per Shelf Carton			5 per Shelf Carton	
		10,000 AIC	22,000 AIC	10,000 AIC	22,000 AIC	42,000 AIC	10,000 AIC	22,000 AIC
Catalog Number	Catalog Number	Catalog Number	Catalog Number	Catalog Number	Catalog Number	Catalog Number		
10	#14 - 4	BR110	—	BR210	—	—	BR310	—
15		BR115 ①②	BRH115	BR215 ③	BRH215	—	BR315 ①②	BRH315 ①②
20		BR120 ①②	BRH120	BR220 ③	BRH220	—	BR320 ①②	BRH320 ①②
25		BR125	BRH125	BR225 ③	BRH225	—	BR325	BRH325
30		BR130	BRH130	BR230 ③	BRH230	—	BR330	BRH330
35	#14 - 4	BR135	BRH135	BR235 ③	BRH235	—	BR335	BRH335
40		BR140	BRH140	BR240 ③	BRH240 ③	—	BR340	BRH340
45		—	BRH145	BR245 ③	BRH245	—	BR345	BRH345
50		BR150	BRH150	BR250 ③	BRH250 ③	—	BR350	BRH350
55	#14 - 3	BR150	BRH155	BR255	BRH255	—	BR355	BRH355
60	#4 - 1/0	BR160	BRH160	BR260	BRH260	BRHH260	BR360	BRH360
70		BR170	BRH170	BR270	BRH270	BRHH270	BR370	BRH370
80		—	—	BR280	BRH280	BRHH280	BR380	BRH380
90		—	—	BR290	BRH290	BRHH290	BR390	BRH390
100		—	—	BR2100	BRH2100	BRHH2100	BR3100	BRH3100
110		—	—	BR2110	BRH2110	BRHH2110	—	—
125	#4 - 2/0	—	—	BR2125	BRH2125	BRHH2125	—	—
150		—	—	BR2150 ④	—	—	—	—

- ① 1-pole, 1-inch (25.4 mm) per pole circuit breakers are available with high magnetic setting for switching large tungsten lamp loads. Add-suffix H to catalog number.
- ② Switching duty rated.
- ③ On the black handle breaker, add suffix "B" to the catalog number to obtain a tapped molded opening for proper use with hold-down kits.
- ④ For use as a branch circuit breaker in 400 and 600 ampere panels only.