

Cord and Cable Fittings

**Straight Body Male Thread
Sealing Gaskets and Locknuts
Sizes 1/2" – 1"**

Cl. I, Div. 2*, Groups A,B,C,D
Cl. II, Div. 1, Groups E,F,G
Cl. II, Div. 2, Groups F,G
Cl. III
Wet Locations*

5F

Complete with locknut, sealing gasket, gland nut and Neoprene bushing



Locknut



Sealing gasket



Body only



Neoprene bushing



Gland nut



Wire mesh grip



5F
Cable and
Cord Fittings

**CGB-SG With Locknut,
Sealing Gasket, Gland Nut and
Tapered Neoprene Bushing †**

Complete with
Locknut, Sealing
Gasket, Gland

Thread Size	Form	Cord Range Dia.	Inside Body Dia.	Complete with Locknut, Sealing Gasket, Gland Nut & Neoprene Bushing ♦	Sealing Gasket Cat. #	Body Only Cat. #	Neoprene Bushing Cat. #	Gland Nut Cat. #	Wire Mesh Grip ♦
1/2	B	.125 to .250	.625	CGB192-SG	SG1	CGB:0104355	BUSH92	NUT94	
1/2	B	.250 to .375	.625	CGB193-SG	SG1	CGB:0104355	BUSH93	NUT94	
1/2	B	.375 to .500	.625	CGB194-SG	SG1	CGB:0104355	BUSH94	NUT94	RPE417-115
1/2	B	.500 to .625	.625	CGB195-SG	SG1	CGB:0104355	BUSH05	NUT94	RPE417-116
1/2	C	.625 to .750†	.625	CGB196-SG	SG1	CGB:1702A	BUSH96	NUT95	RPE417-117
1/2	C	.750 to .875†	.625	CGB197-SG	SG1	CGB:1702A	BUSH97	NUT95	RPE421-119
3/4	C	.625 to .750†	.750	CGB296-SG	SG2	CGB:4318A	BUSH96	NUT95	RPE417-117
3/4	C	.750 to .875†	.750	CGB297-SG	SG2	CGB:4318A	BUSH97	NUT95	RPE421-119
3/4	D	.875 to 1.000†	.813	CGB298-SG	SG2	CGB:4320A	BUSH98	NUT98	16676N
1	C	.500 to .625	.969	CGB395-SG	SG3	CGB:4319A	BUSH95	NUT95	RPE417-129
1	C	.625 to .750	.969	CGB396-SG	SG3	CGB:4319A	BUSH96	NUT95	RPE417-117
1	C	.750 to .875	.969	CGB397-SG	SG3	CGB:4319A	BUSH97	NUT95	RPE421-119
1	D	.875 to 1.000†	1.031	CGB398-SG	SG3	CGB:4321A	BUSH98	NUT98	16676N
1	D	1.000 to 1.188†	1.031	CGB399-SG	SG3	CGB:4321A	BUSH99	NUT98	RPE421-121
1	D	1.188 to 1.375†	1.031	CGB3911-SG	SG3	CGB:4321A	BUSH911	NUT98	RPE433-122

* May be used in hazardous locations with specific cords and cables when installed in accordance with NEC/CEC requirements.

† Remove sufficient outer covering of cord or cable to pass conductors through the connector body.

‡ A wide variety of connectors may be made up using combinations of bodies, gland nuts and Neoprene bushings, providing all parts are of the same form.

♦ Order wire mesh grip separately.

Cord and Cable Fittings

**Straight Body Male Thread
Sealing Gaskets and Locknuts
Sizes 1/2" – 1"**

Cl. I, Div. 2*, Groups A,B,C,D
Cl. II, Div. 1, Groups E,F,G
Cl. II, Div. 2, Groups F,G
Cl. III
Wet Locations*

5F

Complete with locknut, sealing gasket, gland nut and Neoprene bushing

Locknut

Sealing gasket

Body only

Neoprene bushing

Gland nut

Wire mesh grip



5F
Cable and
Cord Fittings

**CGB-SG With Locknut,
Sealing Gasket, Gland Nut and
Tapered Neoprene Bushing ‡**

Complete with
Locknut, Sealing
Gasket, Gland

Thread Size	Form	Cord Range Dia.	Inside Body Dia.	Complete with Locknut, Sealing Gasket, Gland Nut & Neoprene Bushing ♦	Sealing Gasket Cat. #	Body Only Cat. #	Neoprene Bushing Cat. #	Gland Nut Cat. #	Wire Mesh Grip ♦
1/2	B	.125 to .250	.625	CGB192-SG	SG1	CGB:0104355	BUSH92	NUT94	
1/2	B	.250 to .375	.625	CGB193-SG	SG1	CGB:0104355	BUSH93	NUT94	
1/2	B	.375 to .500	.625	CGB194-SG	SG1	CGB:0104355	BUSH94	NUT94	RPE417-115
1/2	B	.500 to .625	.625	CGB195-SG	SG1	CGB:0104355	BUSH05	NUT94	RPE417-116
1/2	C	.625 to .750†	.625	CGB196-SG	SG1	CGB:1702A	BUSH96	NUT95	RPE417-117
1/2	C	.750 to .875†	.625	CGB197-SG	SG1	CGB:1702A	BUSH97	NUT95	RPE421-119
3/4	C	.625 to .750†	.750	CGB296-SG	SG2	CGB:4318A	BUSH96	NUT95	RPE417-117
3/4	C	.750 to .875†	.750	CGB297-SG	SG2	CGB:4318A	BUSH97	NUT95	RPE421-119
3/4	D	.875 to 1.000†	.813	CGB298-SG	SG2	CGB:4320A	BUSH98	NUT98	16676N
1	C	.500 to .625	.969	CGB395-SG	SG3	CGB:4319A	BUSH95	NUT95	RPE417-129
1	C	.625 to .750	.969	CGB396-SG	SG3	CGB:4319A	BUSH96	NUT95	RPE417-117
1	C	.750 to .875	.969	CGB397-SG	SG3	CGB:4319A	BUSH97	NUT95	RPE421-119
1	D	.875 to 1.000†	1.031	CGB398-SG	SG3	CGB:4321A	BUSH98	NUT98	16676N
1	D	1.000 to 1.188†	1.031	CGB399-SG	SG3	CGB:4321A	BUSH99	NUT98	RPE421-121
1	D	1.188 to 1.375†	1.031	CGB3911-SG	SG3	CGB:4321A	BUSH911	NUT98	RPE433-122

* May be used in hazardous locations with specific cords and cables when installed in accordance with NEC/CEC requirements.

† Remove sufficient outer covering of cord or cable to pass conductors through the connector body.

‡ A wide variety of connectors may be made up using combinations of bodies, gland nuts and Neoprene bushings, providing all parts are of the same form.

♦ Order wire mesh grip separately.