

# Definite Purpose Controls Full Voltage Contactors

## Section 4


### CR453C

Compact  
Single Phase  
20A-40A

#### Standard Forms

Standard CR453C contactors feature hex screws with #2 Phillips/slotted heads on the 20-35FLA devices and box lugs on 40FLA forms. Each pole is supplied with four 1/4" quick connect terminals. Coils are provided with two 1/4" quick connect terminals.


For configurations not found below see page 4-5 for Factory Modified Forms.



25A-35A 1 pole



25A-35A  
1 pole + shunt



40A 2 pole

#### CR453C Compact (1, 1 + shunt & 2 pole)

Inductive Amps	Resistive Amps	Locked Rotor Amps, 50/60 Hz @ 240/277V	Locked Rotor Amps, 50/60 Hz @ 480V	Locked Rotor Amps, 50/60 Hz @ 600V	No. of Poles	Product Number	List Price GO-10DP
20	30	120	100	80	1	CR453CA1*AA	\$24.00
20	30	120	100	80	1 + Shunt	CR453CA3*AA	\$29.00
20	30	120	100	80	2	CR453CA2*AA	\$32.00
25	35	150	125	100	1	CR453CB1*AA	\$30.00
25	35	150	125	100	1 + Shunt	CR453CB3*AA	\$36.00
25	35	150	125	100	2	CR453CB2*AA	\$40.00
30	40	180	150	120	1	CR453CC1*AA	\$32.00
30	40	180	150	120	1 + Shunt	CR453CC3*AA	\$38.00
30	40	180	150	120	2	CR453CC2*AA	\$42.00
35	50	180	150	120	1	CR453CD1*AA	\$35.00
35	50	180	150	120	1 + Shunt	CR453CD3*AA	\$44.00
35	50	210	175	140	2 <sup>1</sup>	CR453CD2*AA	\$46.00
40	50	240	200	160	2 <sup>1</sup>	CR453CE2*BB	\$51.00

<sup>1</sup>Ratings shown are for single phase, 2-pole. See page 4-21 for single phase, 1-pole ratings.

(Replace \* in product number with appropriate coil digit.)

#### Coil Selection

##### CR453C Compact Coil Selection

Coil Voltage		Product Number Digit
60 Hz	50 Hz	
24	24	H
110-120	110	A
208-240	208-220	B
277	—	F

