



### Main

Product or component type	Combination Starter
Range of product	S
Control circuit	Common control circuit

### Complementary

[Uc] control circuit voltage	208 V AC 60 Hz
Motor starter type	Non reversing
Poles description	3P
Motor power hp	3 hp 230 V AC 3 phases 3 hp 200 V AC 3 phases
System Voltage	600 V AC
Control type	No control units
Local signalling	No indicator
Auxiliary contact composition	Without
Thermal overload type	Melting alloy 3 Thermal Units
Disconnecter device type	Fusible disconnect switch, Type H Fuse, 30 A
NEMA size	0

### Environment

NEMA degree of protection	NEMA 12 painted sheet steel and without external reset
---------------------------	--

### Offer Sustainability

Not Green Premium product	Not Green Premium product
Will not be Compliant	Will not be Compliant
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

### Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.