

Product datasheet
Characteristics

LAL36200

3P 600VAC/250VDC 200A LAL FA/LA MOLDED CASE CIRCUIT BREAKER



Main

| | |
|---------------------------|------------------|
| Product or component type | Circuit breaker |
| Trip unit technology | Thermal-magnetic |

Complementary

| | |
|--------------------------------|---|
| [In] rated current | 200 A |
| Poles description | 3P |
| Breaking capacity | 42 kA at 240 V AC 30 kA at 480 V AC 22 kA at 600 V AC 10 kA at 125 V DC 10 kA at 250 V DC |
| [Ue] rated operational voltage | 250 V DC 600 V AC |
| Mounting mode | Unit mount |
| Electrical connection | Lugs load Lugs line |
| AWG gauge | AWG 1...600 kcmil (aluminium/copper) 1 cable(s) AWG 1...250 kcmil (aluminium/copper) 2 cable(s) |
| Terminal identifier | AL400LA |
| Magnetic hold current | 1000 A |
| Magnetic tripping current | 2000 A |
| Height | 11 in |
| Width | 6 in |
| Depth | 5.84 in |

Environment

| | |
|------------------------|-------------------------|
| product certifications | CSA IEC UL listed |
|------------------------|-------------------------|

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1304 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.