

Product datasheet
Characteristics

LE1D123A62OG70

FULL-VOLTAGE NON-REVERSING IEC STARTER
UNFUSED TYPE 1



Main

Product or component type	Full voltage starter
Range of product	Instakits
Motor starter type	Non reversing

Complementary

[Ue] rated operational voltage	120 V AC at 50/60 Hz
[Ie] rated operational current AC	12 A
Motor power hp	0.5 hp at 120 V AC for 1 phase motors 2 hp at 240 V AC for 1 phase motors 3 hp at 208 V AC for 3 phases motors 3 hp at 230 V AC for 3 phases motors 7.5 hp at 460 V AC for 3 phases motors 10 hp at 575 V AC for 3 phases motors
[Uc] control circuit voltage	600 V AC
Auxiliary contact composition	1 NO + 1 NC
Location of connection	Line

Environment

product certifications	CSA IEC UL
NEMA degree of protection	NEMA 1 steel

Offer Sustainability

Sustainable offer status	Not Green Premium product
RoHS (date code: YYWW)	Compliant - since 1444 - Schneider Electric declaration of conformity

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.