

Description

The Halo Home In-Wall Smart Dimmer turns standard lights into smart lights. The Smart Dimmer is designed to connect to the Halo Home Bluetooth Mesh network with no hub or internet connection required. The Smart Dimmer can occupy any position in a multi-gang junction box, while the other positions of the junction box can be occupied by switches or other dimmers. The Smart Dimmer can be configured to work with the HALO Home In-wall Accessory dimmer to enable three-way lighting control within a space.

| | | |
|-------------|--|------|
| Catalog # | | Type |
| Project | | |
| Comments | | Date |
| Prepared by | | |

Specification Features

Wireless System

- Utilizes Bluetooth Mesh 4.0
- Wireless range of up to 100 feet from Bluetooth device to device and up to 33 feet from Bluetooth smartphone/tablet to closest device.
- 2.4GHz signal frequency

Wireless Pairing

- See Halo quick start guide for wireless setup, guidance and troubleshooting.

Features

- Control standard lights with the switch or free HALO Home app
- Features ON/OFF, Dimming, Groups, Schedules, and Scenes
- Works with dimmable LEDs, CFL, halogen, and incandescent bulbs and light fixtures

Environmental

- Rated for Indoor Use only. 32°F to 104°F (0°C to 40°C) damp locations

Design Features

- Range: Up to 100 feet line of sight
- Dimmer to have four 6" pre-stripped wire leads for line (black), load (red), ground (green) and neutral (white)
- Air-gap switch disconnects power from load forcing an OFF condition to safely work on the light fixtures.

- Air-gap switch will also disconnect power from the internal circuitry of the dimmer.
- Air-gap switch is a 1 way switch – power is connected through the air-gap switch when the air-gap plastic is in, and power does not go through the air-gap switch when the air-gap plastic is pulled out.
- Neutral wire will be required for installation
- Large paddle switch that actuates 2 switches. Upper part of paddle actuates one switch ON, and lower part of paddle actuates the other switch OFF for ON and OFF functions listed below.
- Thin dimmer rocker switch that also actuates 2 more switches. Upper part of rocker actuates one switch Brighten, and lower part of paddle actuates the other switch Dim for Brighten and Dim functions listed below.
- One status LED under firmware control
- Dimming state shall be retained in the event of AC power loss.
- Acoustic noise not to exceed 22 dBa SPL at 1 ft

Button Functions

- Dim up (Brighten) will brighten the lamps associated to the Accessory Dimmer
- Dim down will dim the lamps associated to the Accessory Dimmer
- ON will turn on the lamps associated to the Accessory Dimmer
- OFF will turn off the lamps associated to the Accessory Dimmer
- Holding the ON button for 12 seconds will factory reset the dimmer and it will also be in Bluetooth pairing mode.

Certifications & Compliance

- cULus Listed, NOM Certified. Complies with FCC Part 15, Class B,
- Industry Canada RSS-Gen and RSS-247
- Title 24 and Title 20 Compliant
- NEMA SSL 7A Compliant type 1 Dimmer
- Bluetooth Certification 4.1 or higher + Mesh
- ROHS-2


Warranty

Five year limited warranty, consult website for details.
www.eaton.com/lighting/legal




HALO Home HIWMA

HALO Home In-wall Smart Dimmer



Single Switch



3-Way or multi-switch



Ordering Information

SAMPLE NUMBER: HIWMA1BLE40AWH

| Device | Generation | Radio | Finish |
|---|------------------|--------------------------------|----------|
| HIWMA = HALO In-Wall Master Dimmer ¹ | 1=1st generation | BLE40=Bluetooth Low Energy 4.0 | WH=White |

1. Wall plate sold separately.

Multi-Unit Installation Chart

| Device | Load Type | 1-Gang | 2-Gang | 3-Gang |
|----------|-------------------------|---------|---------|---------|
| RF9540-N | INC/ELV/FLR/Halogen/MLV | 600W/VA | 550W/VA | 500W/VA |
| | LED/CFL | 300W | 300W | 300W |

| ENERGY DATA | |
|----------------|------|
| Input Voltage | 120V |
| Input Current | - |
| Input Power | 5W |
| Efficiency | - |
| Inrush (A) | - |
| THD: - | |
| PF: - | |
| T Ambient - | |
| Sound Rating - | |