

**Dimmer model numbers**

 **Incandescent/halogen dimmers**

Dimmers

Single-pole 120V 600W	DV-600P- <b>CC</b> <sup>3</sup> DVSC-600P- <b>CC</b> <sup>4</sup>
Single-pole 120V 1000W	DV-10P- <b>CC</b> <sup>3</sup> DVSC-10P- <b>CC</b> <sup>4</sup>
3-way 120V 600W	DV-603P- <b>CC</b> <sup>3</sup> DVSC-603P- <b>CC</b> <sup>4</sup>
3-way 120V 1000W	DV-103P- <b>CC</b> <sup>3</sup> DVSC-103P- <b>CC</b> <sup>4</sup>
3-way/single-pole 120V 600W	DVCL-153P- <b>CC</b> <sup>3</sup>
3-way/single-pole 120V 600W	DVSCCL-153P- <b>CC</b> <sup>4</sup>

Refer to the “how to calculate wattage when mixing lamp types” table on, [www.lutron.com/dimcflled](http://www.lutron.com/dimcflled), when using a combination of bulb types with the C•L™ dimmer.

**eco-dim® dimmer with locator light**

3-way/single-pole 120V 600W	DV-603PG- <b>EE</b> <sup>2</sup>
--------------------------------	----------------------------------

eco-dim model guarantees at least 15% energy savings compared to a standard switch.

 **Dimmable CFL bulbs (screw-base)**

 **Dimmable LED bulbs (screw-base)**

Dimmers

3-way/single-pole 120V 150W	DVCL-153P- <b>CC</b> <sup>3</sup>
3-way/single-pole 120V 150W	DVSCCL-153P- <b>CC</b> <sup>4</sup>

Refer to the “how to calculate wattage when mixing lamp types” table on, [www.lutron.com/dimcflled](http://www.lutron.com/dimcflled), when using a combination of bulb types with the C•L dimmer.

Visit [www.lutron.com](http://www.lutron.com) for an approved list of dimmable CFL/LED bulbs.

 **Magnetic low-voltage dimmers**

Dimmers

Single-pole 120V 600 VA (450W)	DVLV-600P- <b>CC</b> <sup>3</sup> DVSCLV-600P- <b>CC</b> <sup>4</sup>
Single-pole 120V 1000 VA (800W)	DVLV-10P- <b>CC</b> <sup>3</sup> DVSCLV-10P- <b>CC</b> <sup>4</sup>
3-way 120V 600 VA (450W)	DVLV-603P- <b>CC</b> <sup>3</sup> DVSCLV-603P- <b>CC</b> <sup>4</sup>
3-way 120V 1000 VA (800W)	DVLV-103P- <b>CC</b> <sup>3</sup> DVSCLV-103P- <b>CC</b> <sup>4</sup>

The stated VA (Volt-Ampere) rating includes the magnetic transformer heat losses and the lamp load. The stated W (Watt) rating is the maximum lamp wattage based on assumed 20% transformer loss.

**CC**<sup>3</sup>: Gloss color codes, see pg. 87  
**CC**<sup>4</sup>: Satin color codes, see pg. 87  
**EE**<sup>2</sup>: Available in White (WH), Ivory (IV), Almond (AL) and Light Almond (LA)  
 (Wallplates not included with above, order separately, see pg. 160)

All models must be derated if ganged unless otherwise noted, see pg. 170.