



Two Piece SpringLamps

TWO PIECE REPLACEMENT LAMPS, TCX BASE, PL 4-PIN, AMALGAM, 10,000 HOUR




Item Number	ENERGY STAR® Item Description	Lamp Watts	Incandescent Comparison (Watts)	Initial Lumens	CCT (Kelvin)	CRI	MOL/Height (Inches)	Diameter/Width (Inches)	Base Type	Case Quantity
35009M	9 Watt Mini-SpringLamp Replacement	9	40	550	2700	82	3.0	1.8	TCX 4-pin	12
35011M	11 Watt Mini-SpringLamp Replacement	11	52	650	2700	82	3.0	1.8	TCX 4-pin	12
35014M	14 Watt Mini-SpringLamp Replacement	14	60	900	2700	82	3.1	1.8	TCX 4-pin	12
35009	9 Watt SpringLamp Repl	9	35	400	2700	82	2.6	2.2	TCX 4-pin	12
35011	11 Watt SpringLamp Repl	11	40	550	2700	82	2.8	2.2	TCX 4-pin	12
35015	15 Watt SpringLamp Repl	15	60	930	2700	82	3.1	2.2	TCX 4-pin	12
35018	18 Watt SpringLamp Repl	18	75	1150	2700	82	3.4	2.2	TCX 4-pin	12
35020	20 Watt SpringLamp Repl	20	75	1200	2700	82	3.4	2.2	TCX 4-pin	12
35023	23 Watt SpringLamp Repl	23	90	1400	2700	82	3.7	2.2	TCX 4-pin	12
35026	26 Watt SpringLamp Repl	26	100	1750	2700	82	4.3	2.2	TCX 4-pin	12
35032	32 Watt SpringLamp Repl	32	125	2100	2700	82	4.8	2.2	TCX 4-pin	12
35042	42 Watt SpringLamp Repl	42	150	2800	2700	82	5.6	2.5	TCX 4-pin	12

SPRINGLAMP DIMMABLE REPLACEMENT LAMPS, TCX BASE, PL 4-PIN AMALGAM, 10,000 HOUR



36009	9 Watt SpringLamp	9	35	400	2700	82	2.6	2.2	TCX 4-pin	12
36015	15 Watt SpringLamp	15	60	930	2700	82	3.1	2.2	TCX 4-pin	12
36018	18 Watt SpringLamp	18	75	1150	2700	82	3.4	2.2	TCX 4-pin	12
36020	20 Watt SpringLamp	20	75	1200	2700	82	3.4	2.2	TCX 4-pin	12

TWO PIECE REPLACEMENT LAMPS, ANSI BASE, PL 4-PIN, AMALGAM, 10,000 HOUR



33009M	9 Watt Mini-SpringLamp	9	40	550	2700	82	3.0	1.8	G24Q-1	12
33014M	14 Watt Mini-SpringLamp	14	60	900	2700	82	3.1	1.8	G24Q-1	12
33015	15 Watt SpringLamp	15	60	930	2700	82	3.7	2.2	G24Q-1	12
33018	18 Watt SpringLamp	18	75	1150	2700	82	4.0	2.2	G24Q-2	12
33020	20 Watt SpringLamp	20	75	1200	2700	82	4.0	2.2	G24Q-2	12
33023	23 Watt SpringLamp	23	90	1400	2700	82	4.2	2.2	G24Q-3	12
33026	26 Watt SpringLamp	26	100	1750	2700	82	4.8	2.2	G24Q-3	12
33032	32 Watt SpringLamp	32	125	2100	2700	82	5.3	2.2	G24Q-3	12
33042	42 Watt SpringLamp	42	150	2800	2700	82	5.6	2.5	G24Q-3	12