



**12013 BZ**  
Fixture  
shown in Bronze

STEP

**1**  
**SELECT APPROPRIATE  
LIGHT FIXTURE  
SIZE & FINISH.**

TaskWork Direct Wire 120 Volt Xenon design features large wiring compartments and multiple 1/2" trade-size knockouts for fast and easy installation.

**AVAILABLE FINISHES**

*painted Bronze (BZ), Silver (SI) and White (WH)*



**12011 BZ, SI, WH**

- 1 light, 7" L x 5" W x 1-1/4" H
- 120 Volt, 20 Watt Xenon bulb included

**12012 BZ, SI, WH**

- 2 light, 12" L x 5" W x 1-1/4" H
- 120 Volt, 20 Watt Xenon bulbs included

**12013 BZ, SI, WH**

- 3 light, 22" L x 5" W x 1-1/4" H
- 120 Volt, 20 Watt Xenon bulbs included

**12014 BZ, SI, WH**

- 4 light, 30" L x 5" W x 1-1/4" H
- 120 Volt, 20 Watt Xenon bulbs included

**Replacement Bulbs**

**12090 CLR – Replacement Bulb**

- 120 Volt, 20 Watt Xenon, clear

**BACK MOUNT DESIGN**



**FEATURES**

- 1-1/4" Profile x 5" W
- 120 Volt, 20 Watt Xenon bulb(s)
- Painted Bronze, Silver or White finish
- High/Low/On-Off Switch
- cUL Listed

**PERFORMANCE DATA (12012)**

	<b>LUMENS/WATT</b>	<b>5</b>	
<b>A</b>	<b>LIGHT OUTPUT FC (COUNTER FRONT)</b>	<b>8.6</b>	
<b>B</b>	<b>LIGHT OUTPUT FC (COUNTER MIDDLE)</b>	<b>21.1</b>	
<b>C</b>	<b>LIGHT OUTPUT FC (COUNTER BACK)</b>	<b>38.2</b>	
<b>D</b>	<b>LIGHT OUTPUT FC (COUNTER WALL)</b>	<b>13.2</b>	
	<b>CRI (COLOR RENDERING)</b>	<b>100</b>	
	<b>CCT (COLOR TEMPERATURE)</b>	<b>2620K</b>	
	<b>LIGHT SOURCE LIFE (HRS)</b>	<b>2,500</b>	

