

# 5F

## Cord and Cable Fittings

### Straight Body Male Thread

Sizes 3/8" – 3"

Cl. I, Div. 2\*, Groups A,B,C,D

Cl. II, Div. 1, Groups E,F,G

Cl. II, Div. 2, Groups F,G

Cl. III


Wet Locations

Cable and Cord Fittings  
5F

Complete with gland nut and Neoprene bushing



Body only



Neoprene bushing



Gland nut



**CGB With Gland Nut and Tapered Neoprene Bushing†**

Thread Size	Form	Cord Range Dia.	Inside Body Dia.	Complete with Gland Nut & Neoprene Bushing ♦ Cat. #	Body Only Cat. #	Neoprene Bushing Cat. #	Gland Nut Cat. #	Wire Mesh Grip ♦ Cat. #
1	B	.250 to .375	.688	CGB393§	CGB:19478A	BUSH93	NUT94	
1	B	.375 to .500	.688	CGB394§	CGB:19478A	BUSH94	NUT94	RPE417-115
1	C	.500 to .625	.969	CGB395§	CGB:4319A	BUSH95	NUT95	RPE417-129
1	C	.625 to .750	.969	CGB396§	CGB:4319A	BUSH96	NUT95	RPE417-117
1	C	.750 to .875	.969	CGB397§	CGB:4319A	BUSH97	NUT95	RPE421-119
1	C	.875 to 1.000†	.969	CGB3239§	CGB:4319A	BUSH239	NUT95	RPE421-120
1	D	.875 to 1.000†	1.031	CGB398§	CGB:4321A	BUSH98	NUT98	16676N
1	D	1.000 to 1.188†	1.031	CGB399§	CGB:4321A	BUSH99	NUT98	RPE421-121
1	D	1.188 to 1.375†	1.031	CGB3911§	CGB:4321A	BUSH911	NUT98	RPE433-122
1¼	D	.875 to 1.000	1.250	CGB498	CGB:4322A	BUSH98	NUT98	16676N
1¼	D	1.000 to 1.188	1.250	CGB499	CGB:4322A	BUSH99	NUT98	RPE421-121
1¼	D	1.188 to 1.375†	1.250	CGB4911	CGB:4322A	BUSH911	NUT98	RPE433-122
1¼	E	1.375 to 1.625†	1.250	CGB4913	CGB:5472B	BUSH913	NUT913	RPE433-123
1¼	E	1.625 to 1.875†	1.250	CGB4915	CGB:5472B	BUSH915	NUT913	17317N
1½	D	.875 to 1.000	1.438	CGB598	CGB:5397B	BUSH98	NUT98	16676N
1½	D	1.000 to 1.188	1.438	CGB599	CGB:5397B	BUSH99	NUT98	RPE421-121
1½	D	1.188 to 1.375	1.438	CGB5911	CGB:5397B	BUSH911	NUT98	RPE433-122
1½	E	1.375 to 1.625†	1.438	CGB5913	CGB:5473B	BUSH913	NUT913	RPE433-123
1½	E	1.625 to 1.875†	1.438	CGB5915	CGB:5473B	BUSH915	NUT913	17317N
2	E	1.375 to 1.625	1.875	CGB6913	CGB:5474B	BUSH913	NUT913	RPE433-123
2	E	1.625 to 1.875†	1.875	CGB6915	CGB:5474B	BUSH915	NUT913	17317N
2	F	1.875 to 2.188†	1.875	CGB6917	CGB:5475B	BUSH917	NUT917	17345N ♦♦
2	F	2.188 to 2.500†	1.875	CGB6920	CGB:5475B	BUSH917	NUT917	16772N ♦♦♦
2½	E	1.375 to 1.625	2.062	CGB7913	CGB:1278B	BUSH913	NUT913	RPE433-123
2½	E	1.625 to 1.875	2.062	CGB7915	CGB:1278B	BUSH915	NUT913	17317N
2½	F	1.875 to 2.188	2.313	CGB7917		BUSH917		17345N ♦♦
2½	F	2.188 to 2.500	2.313	CGB7920		BUSH920		16772N ♦♦♦
3	F	1.875 to 2.188	2.750	CGB8917		BUSH917		17345N ♦♦
3	F	2.188 to 2.500	2.750	CGB8920		BUSH920		16772N ♦♦♦

Wire mesh grip



**NOTE: Use CGFP series on page 73 for larger sizes.**

**See page 64 for dimensions.**

§ Available in copper-free aluminum. To order, add suffix SA to Cat. No.

\* May be used in hazardous locations with specific cords and cables when installed in accordance with NEC/CEC requirements.

† Remove sufficient outer covering of cord or cable to pass conductors through the connector body.

‡ A wide variety of connectors may be made up using combinations of bodies, gland nuts and Neoprene bushings providing all parts are of the same form.

◆ Order wire mesh grip separately.

**Diameter Cord Range**

**Wire Mesh Grip**

◆◆ 1.875 to 2.000

◆◆◆ 2.000 to 2.250

**Neoprene Bushing**

1.875 to 2.188

2.188 to 2.500